



## **Digital-1 Consultant Specs**

The receiver shall operate in the 72-76MHz Auditory Assistance Band as approved by the FCC. It shall be digitally tunable to one of 37 frequencies within that band by concealed rotary switches.

The receiver shall be housed in a high-strength, plastic case with integral pocket clip. The On/Off/Volume control shall be properly marked and the only control that is exposed. There shall be a standard 1/8" mono headphone jack for audio output. The jack shall be recessed to provide stress protection for the headphone plug.

Audio frequency response shall be 100Hz-10kHz. The receiver shall provide an audio output of 140mW into a 32Ω load. The receiver shall operate on two standard AA batteries, and contain built-in recharging contacts for operation with rechargeable batteries and a suitable drop-in recharger.

The Gentner Digital-1 Receiver is specified.