



Venture-6 Consultant Specs

The receiver shall operate in the 216 MHz Auditory Band as approved by the FCC. Audio frequency response shall be 100-10,000Hz.

The Receiver shall have a thumb wheel switch to select any of six preset channels in the Auditory Band. Each of the six preset channels shall be individually tunable via an internal control. The receiver shall be contained in a simple, high-strength plastic case with integral pocket clip. Only the ON/OFF/VOLUME and channel control shall be exposed. There shall be a standard 1/8" mono headphone jack for audio output. The jack shall be recessed to provide stress protection for the headphone plug.

The receiver shall provide an audio output of 140mW into a 32Ohm load. The receiver shall operate on two standard AA batteries, and contain built-in recharging contacts for operation with rechargeable batteries and a suitable drop-in recharger.

The Gentner Venture-6 receiver is specified.